

## SWITCHLITE MRE SLD

### PIR detector with photocell

Art. no. 96218677

#### Application

The SWITCHLITE MRE SLD recessed PIR Presence Detector provides energy saving (on/off switching) in response to room occupancy and daylight levels, controlling standard luminaires containing wound gear or high frequency fixed output ballasts.

Cost effective in applications such as cellular offices or areas which are unoccupied for long periods of time, such as storerooms or toilets.

Suitable for indoor use only.

#### Design notes

- It is simply converted to a surface version by adding the surface mounting attachment kit SWITCHLITE KIT MSF (96 218 678), available as accessory.
- To switch from more than one position simply wire two or more units in parallel.
- The detector should be sited so that the occupants of the room fall inside the detection pattern, at a recommended height of 2.8m on the ceiling. Note that the lower the sensor is installed the smaller the detection range will be.
- Avoid direct sunlight entering the sensor.
- Do not site within 1m of forced air heating or ventilation, or any lighting.
- Do not fix to a vibrating surface.



#### Functional description

- Covers up to 7 metres diameter at a 2.8m mounting height
- Minimum ambient light level can be adjusted to ensure luminaires are switched on when required.
- If daylight is sufficient (the ambient light above the minimum level) and somebody enters the sensor's detection zone, the luminaires remain switched Off.
- If the daylight is insufficient (the ambient light below the minimum level) and somebody enters or is in the sensor's detection zone, the luminaires will be switched On, and will stay switched On as long as presence is detected.
- Provides additional building security by switching on when intruders are detected.
- An adjustable time delay before switching luminaires off provides flexibility for the user (10s to 30min)
- Reducing building running costs
- Recessed design provides minimum intrusion

### Mounting and installation instructions

- The detector should be sited so that the occupants of the room fall inside the detection pattern, at a recommended height of 2.8m on the ceiling.
- Avoid direct sunlight entering the sensor.
- Do not site within 1m of forced air heating or ventilation, or any lighting.
- Do not fix to a vibrating surface.
- Cut 64Ø hole into the ceiling
- Insert the mounting clip into the hole and carefully push the two fixings on the arms downwards until they grip firmly to the ceiling, ensuring its retention.
- Detach the mains cover of the sensor, plug in the connector and replace the cover.
- Loosely push the unit into the clip, set timing and light level and fit into ceiling, sliding the detector onto the sleeve.

### Technical data

Supply voltage	230...240V AC
Switching capacity	8A resistive, or 6A capacitive or inductive, or 8 HF electronic ballasts, or 3A with compact fluorescent lamps 8 Amp resistive and incandescent lighting, 6 Amp fluorescent lighting, 3 Amp compact fluorescent lighting, 3 Amp low energy lighting, 3 Amp low voltage lighting (switch primary of transformer) Fluorescent lighting (max 6 fittings recommended) 3 Amp fans and ventilation equipment Switch SON lighting loads via a contactor
Presence monitoring range	approx 5...7m diameter at 2.5m ceiling height
Miscellaneous	Time delay 10s...30min adjustable
Terminals	2.5mm <sup>2</sup>
Housing material	Flame retardant ABS, fixing clip polypropylene
Protection class	Class II
Permitted ambient temperature	-10 °C ... +35 °C
Weight	Approx. 0.15 kg