



Representative Photo Only
(actual product may vary based on configuration selections)

Star Delta Starter 37...45KW, With 18...90A Electronic Overload, Open Type, Control Voltage 415V AC, Adjustable Changeover Time (1.5...30 Seconds)

- Wide range of NHP motor starting method versions available, allowing for correct selection of a motor starter to suit the application load condition requirements during starting
- Available in a number of IP ratings and enclosure type, to allow selection to meet the different installation environments
- Overload is to be set to 58% of the motor Full Load Current (FLC)
- **Consult NHP for complete offering**

SPECIFICATIONS

Product Series	Streamline Enclosed Motor Starters
kW Rating, AC-3, 415V, Min	37 kW @415V min
kW Rating, AC-3, 415V, Max	45 kW @415V max
Component Type Motor Control and Drives	Star-Delta Starter
Details, Contactor, Main	CA7-60 Main
Details, Contactor, Delta	CA7-60 Delta
Details, Contactor, Star	CA7-30 Star
Motor FLC, Min	18 A, min
Motor FLC, Max	90 A, max
IP Rating	IP00
Motor Connection	6 wire
Enclosure Type	Open type
Control Voltage, AC, Nom	415 V AC

REFERENCES

IECEx Certificate	-
Supplier Declaration of Conformity:	-
Installation Guide:	-
User Manual:	-
Manufacturer Datasheet:	-
Manufacturer Catalogue & Product Selection:	-