



PIXIE SMART SWITCH SWL350BT

Bluetooth push button lighting switch

Application

Smart lighting controls with blue-tooth connectivity for residential and commercial spaces

Design Specifications

- FEATURES: When used independently- Push on/off ,
- WITH THE "PIXIE" APP TIMER FUNCTION: set switches or switch groups to remain on for set time period SCHEDULE FUNCTION: set switches or switch groups to turn off, turn on at set times and days of the week. GROUP FUNCTION: group switches together into switch groups SCENE FUNCTION: set up a range of switch level scenarios (scenes) by individual switches, or switch groups
- Fit most branded switch plates. 1, 2 or 3 gang, (dimension L x H1 X H2 X W) 40 x 34 x 45 x 22.5mm
- Overheating, overload and full short circuit protection, maximum load 350 watt, minimum load 13 watt.
- SMART LED indicator
- Complies to AS/NZS 60669.2.1, typical wireless range 15 metres




Technical Specification

Model No.	Description	Input (V)	Power (W)
SWL350BT	BLUETOOTH SMART SWITCH 350W	240	350

Dimensions

SDD350BT



SDD350BT

